



## DESIGNED TO DELIVER CUSTOMIZED APPLICATIONS FOR SPECIFIC BUSINESS NEEDS

Capture, create, and communicate at network speed with the Canon imageRUNNER<sup>®</sup> 5070. From high-speed scanning and local document storage to advanced finishing, electronic distribution, and Internet-ready capabilities, the imageRUNNER 5070 delivers unmatched performance, durability, and innovation.

Delivering output at speeds of up to 50 pages per minute (letter), the imageRUNNER 5070 features Canon's MEAP® (Multifunctional Embedded Application Platform) architecture as well as enhanced device management and security features. Send enhancements allow you to distribute documents instantaneously while usability improvements ensure ease-of-use. Plus, this device supports integration with Web-based information systems. With all these advanced features–and more–your office can achieve a new level of performance with the imageRUNNER 5070.

## imageRUNNER 5070 Specifications

Туре:	Digital, Multifunction Imaging System	Accessories		Saddle-stitching (Saddle Finisher-T2 Only)	
Imaging System:	Laser Dry Electrostatic Transfer			Acceptable Paper Sizes:	Letter-R, Legal, 11" x 17"
Developing System:	Dry Mono Component Developing	Universal Send™ Kit-D1 (Optional)		Capacity/Tray:	1 to 5 Sheets/25 Sets
	System	Sending Methods:	E-mail, I-fax, Super G3 Fax (Optional), File Server (IPX, FTP, SMB), User Inbox		6 to 10 Sheets/15 Sets 11 to 15 Sheets/10 Sets
Fixing System:	Induction Heating Fusing System	Address Book Capacity:	Max. 1,800 Destinations	Max. Stapling Capacity/Set:	15 Sheets
Image Server Memory:	Standard 512MB RAM/20GB HDD	File Format		Folding:	V-fold
First-copy Time:	Approx. 3.3 Seconds or Less From	Standard:	TIFF, PDF,	Dimension (H x W x D):	42-3/4" x 25-1/2" x 25-7/8"
	Platen Glass	Optional:	PDF (OCR)	Weight	(1,085mm x 648mm x 657mm)
Warm-up Time:	Approx. 30 Seconds or Less	Sending Sizes:	Statement to 11" x 17"	Finisher T1:	Approx. 88.2 lb. (40kg)
Copy/Print Speed:	50 cpm/ppm (Letter)			Saddle Finisher T2:	Approx. 163 lb. (74kg)
Acceptable Originals:	Sheets, Books, 3-dimensional Items	Duplexing Automatic Document		Attachable Accessories:	Puncher Unit-M1
Acceptable Orginals:		Acceptable Originals:	Statement to 11" x 17"		
	(Up to 4.4 lb.)	Capacity:	100 Sheets (20 lb. Bond)	Puncher Unit-M1 (Option for Finis	
Max. Original Size:	11" x 17"	Original Paper Weight:	13 lb. to 32 lb. Bond	Max. Paper Weight:	17 lb. Bond to 110 lb. Index
Max. Copy Size:	11" x 17"	Feeding Speed: Power Source:	65 Sheets/Minute (Letter) From Main Unit	Paper Sizes 2-hole:	Letter-R, Legal, Executive
Min. Copy Size:	3-7/8" x 5-7/8"	Fower Source:	FION Main Onit	3-hole:	Letter, 11" x 17"
Max. Mail Boxes Supported:	100	Copy Tray-L1 (Optional)		Punch Method:	Sequential Processing System
Max. Copy Reservation:	5 Jobs	Capacity:	250 Sheets (20 lb. Bond)		(One sheet at a time)
Actual Resolution:	600 x 600 dpi	Dimension (H x W x D):	7-3/8" x 17-5/8" x 13-3/8"	Punch Dust Stock:	3,000 Sheets
Interpolated Resolution:	1200 x 600 dpi (Copy)		(186mm x 446mm x 340mm)	Power Source:	From Main Unit
	2400 x 600 dpi (Print)		(When auxiliary tray and auxiliary	Dimension (H x W x D):	32-3/4" x 4-1/4" x 24-1/2"
Halftones:	256 Gradations		wire are extended)	Wainht	(833mm x 107mm x 614.8mm)
		Weight:	Approx. 1.4 lb. (670g)	Weight:	Approx. 15.9 lb. (7.2kg)
Duplexing:	Standard Automatic Trayless			Paper Deck-V1 (Optional)	
	Duplexing	Finisher-T1 and Saddle Finisher-		Number of Drawers:	1
Magnification:	25% to 400% (Platen)	Number of Trays:	3 Trays	Paper Capacity:	3,500 Sheets (20 lb. Bond)
	25% to 200% (Feeder)	Tray Capacity		Paper Size:	Letter
	(in 1% Increments)	No-collate Mode Tray A:	250 Sheets (Letter, Statement-R,	Paper Weight:	17 lb. Bond to 110 lb. Index
Exposure Control:	Automatic or Manual (9 Levels)	IIdy A:	Executive)	Power Source:	From Main Unit
Paper Sources			125 Sheets (Legal, Letter-R, 11" x 17")	Dimension (H x W x D):	22-5/8" x 12-3/4" x 23" (574mm x 323mm x 583mm)
Standard:	Dual Front-loading Trays	Tray B:	1,300 Sheets (Letter, Statement-R,	Weight:	Approx. 101 lb. (46kg)
	(1,500 Sheets Each)		Executive)		
	Dual Front-loading Cassettes		650 Sheets (Legal, Letter-R, 11" x 17")	Super G3 Fax Board-R1 (Optional)	
	(550 Sheets Each)	Tray C:	2,450 Sheets (Letter, Executive)	Applicable Line:	Public Switched Telephone Network (PSTN)
	50-sheet Stack Bypass		1,700 Sheets (Statement-R) 650 Sheets (Legal, Letter-R, 11" x 17")	Connection Lines:	1
Optional:	3,500-sheet Paper Deck	Collate and Group Mode	650 Sheets (Legal, Letter-R, 11 X 17 )	Sending/Original Size:	- Statement to 11" x 17"
optional	(Total: 7,650 Sheets)	Tray B:	1,300 Sheets (Letter, Executive)	Recording/Printing Size:	Statement to 11" x 17"
			650 Sheets (Legal, Letter-R, 11" x 17")	Transmission Times**	
Multiple Copies:	1 to 999	Tray C:	1,700 Sheets (Letter, Executive)	ECM-MMR:	Approx. 3.2 Seconds
Paper Weights (From All Sources):			650 Sheets (Legal, Letter-R, 11" x 17")	G3MR:	Approx. 13 Seconds
Dimensions (H x W x D):	47" x 25-3/8" x 29-1/4"	Staple Mode		G3MH: JBIG:	Approx. 13 Seconds Approx. 2.6 Seconds
	(1192mm x 643mm x 743mm)	Tray B/C:	1,300 Sheets/100 Sets (Letter,	Scan Line Density	Approx. 2.0 Seconds
Weight:	Approx. 474 lb. (215kg)		Executive)	Standard:	8 pels/mm x 3.85 lines/mm
Power Requirements:	120VAC, 60Hz, 16A		650 Sheets/50 Sets (Legal, Letter-R,	Fine:	8 pels/mm x 7.7 lines/mm
Power Consumption:	1.85kW (Max.)		11" x 17")	Super-Fine:	8 pels/mm x 15.4 lines/mm
Plug:	NEMA 5-20R	Max. Stapling Capacity	FO Shorts (Letter 5 11 )	Ultra-Fine:	16 pels/mm x 15.4 lines/mm
Toner Yield:	45,000 Images (at 6% Coverage)	Corner/Double:	50 Sheets (Letter, Executive)	Auto Dial Function:	Address Book: 1,800 Destinations
		1	30 Sheets (Letter-R, Legal, 11" x 17")	Image Memory:	Approx. 8,000 Pages



## imageRUNNER<sup>®</sup> 5070

Paper Deck-V1

## imageRUNNER 5070 Specifications (Continued)

Processor:       Canon Custom Processor-Shared       PS:       136 Scalable Fonts,       0 Document Tray-K1         Memory:       512MB—Shared       PCL Se/6:       80 Scalable Fonts, 30 Barcode Fonts,       0 ECopy Suite         Storage:       20GB—Shared       2 OCR Fonts, 10 Bitmap Fonts       • Ecopy Suite         PDL Support:       PCL Se/6, PostStrift* 3TM       Utility Software:       NetWork ScanGear       • imageRUNNER Security Kit-A2         Emulation, UFR II (Ultra Fast Rendering)       Remote UI <sup>TM</sup> • NetSpot*Console,       • NetSpot*Console,         Interface Connections       USB 2.0 High Speed       NetSpot Resource Downloader       • Tab Feeding Attachment-A1         USB 2.0 High Speed       NetSpot Device Installer       • USB Class Driver, Fax Driver       • UsB Application Interface Board-D1         Network OS:       Windows NT* 4.0/Server 2003       Solaris*** 1.1X, 2.5 x or later       • Voice Guidance Kit-A2         Network Privers       Macintosh* 05 8.0 or later (PPD)       Canon NDPS Gateway       • Voice Status Extension)         Printer Drivers       Windows Strev 2003       Solaris*** 1.1X, 2.5, x or later       Canon Watermark Add-in         UFR II:       Windows 200/XP       Kindows Sone Conversion Utility       Kinderise Book Conversion Utility         UFR II:       Windows 2000/XP       Kindows Sone 2003       Kindows		
Storage:20GB-Shared2 0 CR Fonts, 10 Bitmap Fonts• Expansion Bus Board-C1PDL Support:PCL 5e/6, PostScript® 3™Utility Software:Network ScanGear• imageRUNNER Security Kit-A2Emulation, UFR II (Ultra Fast Rendering)Remdering)Netspot © console,• NetSpot SoulaInterface Connections10/100Base-TX (R)-45), USB 2.0 High SpeedNetSpot P Console,• NetSpot SoulaNetwork OS:Windows® 98/Me/2000/XP Windows N™ 4.0/Server 2003 		
PDL Support:     PCL 5e/6, PostScript® 3™     Utility Software:     Network ScanGear     imageRUNNER Security Kit-A2       Emulation, UFR II (Ultra Fast Rendering)     Remote UI™     imageWARE™ Suite     imageWARE™ Suite       Interface Connections     NetSpot® Console,     imageWARE™ Suite     imageWARE™ Suite       Standard:     10/100Base-TX (R)-45),     NetSpot Besource Downloader     imageWare™ Software Kit-A1       USB 2.0 High Speed     NetSpot Device Installer     uSB 2.0 High Speed     iuniversal Send PDF Enhancement A1       Network OS:     Windows 98/Me/2000/XP     JBIG ImageViewer     iuniversal Send PDF Enhancement Kit-B1       Network OS:     Windows NT® 4.0/Server 2003     Canon LPR 2     iuniversal Send PDF Enhancement Kit-B1       Macintosh® 0S & 0 or later (PPD)     Canon Font Manager     iuniversal Send PDF Enhancement Kit-B1       Network Scongent     DSE (Device Status Extension)     Address Book Conversion Utility       Printer Drivers     Windows S2000/XP     DSE (Device Status Extension)       UFR II:     Windows Server 2003     Mindows Server 2003     Hindew Server 2003       Citrix MetaFrame     Windows Server 2003     Litrix MetaFrame     Hindew Server 2003		
Emulation, UFR II (Ultra Fast Rendering)Remote UITM• imageWARETM SuiteInterface ConnectionsNetSpot® Console, NetSpot Job Monitor• NetSpot SuitwStandard:10/100Base-TX (R)-45), UB2.0 High SpeedNetSpot Resource Downloader 		
Rendering)       NetSpot * Console,       • NetSpot Suite         Interface Connections       NetSpot Job Monitor       • Remote Operator's Software Kit-A1         Standard:       10/100Base-TX (RJ-45),       NetSpot Resource Downloader       • Tab Feeding Attachment-A1         USB 2.0 High Speed       USB 2.0 High Speed       USB Class Driver, Fax Driver       • USB Application Interface Board-D1         Network OS:       Windows % 98/Me/2000/XP       JBIG ImageViewer       • USB Class Driver, Fax Driver         Vindows NT* 4.0/Server 2003       Canon LPR 2       • Web Access Software-A1         Solaris™ 1.1x, 2.5x or later       Canon NDPS Gateway       • Web Access Software-A1         NetWork DF       NetWare* v.3.2, 4.1, 4.11, 4.2,       Canon Watermark Add-in       • Web Access Software-A1         Printer Drivers       Mindows Server 2003       Canon Watermark Add-in       • Web Access Software-A1         UFR II:       Windows Server 2003       Address Book Conversion Utility       • Het Spot Equit Control Eq		
Interface Connections       NetSpot Job Monitor       • Remote Operator's Software Kit-A1         Standard:       10/100Base-TX (RI-45), USB 2.0 High Speed       NetSpot Resource Downloader       • Tab Feeding Attachment-A1         VSB 2.0 High Speed       USB 2.0 High Speed       USB Class Driver, Fax Driver       • USB Application Interface Board-D1         Network OS:       Windows® 98/Me/2000/XP       USB Class Driver, Fax Driver       • Universal Send PDF Enhancement Kit-B1         Network OS:       Windows NT® 4.0/Server 2003       Canon LPR 2       • Web Access Software-A1         Solaris™ 1.1x, 2.5x or later       Canon NDPS Gateway       • Web Access Software-A1         Macintosh® OS 8.0 or later (PPD)       Canon Font Manager       • Web Access Software-A1         NetWare® v.3.2, 4.1, 4.11, 4.2,       Canon Watermark Add-in       • Web Access Software-A1         Printer Drivers       Address Book Conversion Utility       • Hende Guerator's Software Kit-A2         UFR II:       Windows Server 2003       Address Book Conversion Utility       • Hende Guerator's Software Kit-A1         UFR II:       Windows Server 2003       Ether Kit-A1       • USB Application Interface Board-D1         UFR II:       Windows Server 2003       Ether Kit-A1       • USB Application Interface Board-D1         UFR II:       Windows Server 2003       Ether Kit-A1       • USB Application Int		
Standard:     10/100Base-TX (R)-45), USB 2.0 High Speed     NetSpot Resource Downloader NetSpot Device Installer     • Tab Feeding Attachment-A1       USB 2.0 High Speed     USB 2.0 High Speed     • USB 2.0 High Speed       Network OS:     Windows® 98/Me/2000/XP Windows NT® 4.0/Server 2003     USB Class Driver, Fax Driver     • Universal Send PDF Enhancement Kit-B1       Solaris™ 1.1x, 2.5x or later     Canon LPR 2     • Voice Guidance Kit-A2       Macintosh® OS 8.0 or later (PPD)     Canon Font Manager     • Web Access Software-A1       NetWork Direr     Canon Watermark Add-in     • Web Access Software-A1       Printer Drivers     Address Book Conversion Utility     • Hab Feeding Attachment At       Windows Server 2003     Canon Hort Server Status Extension)     Address Book Conversion Utility       UFR II:     Windows Server 2003     Eth Ken		
USB 2.0 High Speed     NetSpot Device Installer     • USB Application Interface Board-D1       Network OS:     Windows*98/Me/2000/XP     USB Class Driver, Fax Driver     • Universal Send PDF Enhancement Kit-B1       Network OS:     Windows NT* 4.0/Server 2003     Canon LPR 2     • Voice Guidance Kit-A2       Solaris™ 1.1x, 2.5x or later     Canon NDPS Gateway     • Web Access Software-A1       Novell* NetWare* v.3.2, 4.1, 4.11, 4.2,     Canon NDPS Gateway     • Voice Guidance Kit-A2       Novell* NetWare* v.3.2, 4.1, 4.11, 4.2,     Canon NDPS Gateway     • Voice Guidance Kit-A2       Printer Drivers     Address Book Conversion Utility     • Voice Guidance Kit-A2       UFR II:     Windows 2000/XP     Address Book Conversion Utility     • Voice Guidance Kit-A2       Windows Server 2003     Citrix MetaFrame     Canon Hort Server 2003     • Voice Guidance Kit-A2		
Network OS:     Windows® 98/Me/2000/XP     USB Class Driver, Fax Driver     • Universal Send PDF Enhancement Kit-B1       Network OS:     Windows NT® 4.0/Server 2003     Canon LPR 2     • Web Access Software-A1       Solaris™ 1.1x, 2.5x or later     Canon NDPS Gateway     • Web Access Software-A1       Macintosh® OS 8.0 or later (PPD)     Canon Font Manager     • Web Access Software-A1       Novell® NetWare® v.3.2, 4.1, 4.11, 4.2,     Canon Watermark Add-in     • Web Access Software-A1       Printer Drivers     Address Book Conversion Utility     • Windows Server 2003       UFR II:     Windows Server 2003     Ethics       Citrix MetaFrame     Ethics     • Windows Server 2003		
Network OS:     Windows® 98/Me/2000/XP     JBIG ImageViewer     • Voice Guidance Kit-A2       Windows NT® 4.0/Server 2003     Canon LPR 2     • Web Access Software-A1       Solaris™ 1.1x, 2.5x or later     Canon NDPS Gateway     • Woice Guidance Kit-A2       Macintosh® OS 8.0 or later (PPD)     Canon Font Manager     • Web Access Software-A1       Novell® NetWare® v.3.2, 4.1, 4.11, 4.2,     Canon Watermark Add-in     • Web Access Software-A1       Printer Drivers     Address Book Conversion Utility     • Windows SonO/XP       Windows Server 2003     Citrix MetaFrame     • Uice Guidance Kit-A2		
Windows NT® 4.0/Server 2003     Canon LPR 2     • Web Access Software-A1       Solaris™ 1.1x, 2.5x or later     Canon NDPS Gateway     • Web Access Software-A1       Macintosh® OS 8.0 or later (PPD)     Canon Font Manager     • Web Access Software-A1       Novell® NetWare® v.3.2, 4.1, 4.11, 4.2,     Canon Watermark Add-in     • Web Access Software-A1       5, 5.1, 6, 6.5 (IPX/SPX™)     DSE (Device Status Extension)     • Mediress Book Conversion Utility       UFR II:     Windows 2000/XP     Mindows Server 2003     • Windows Server 2003       Citrix MetaFrame     • Windows Server 2003     • Windows Server 2003		
Solaris™ 1.1x, 2.5x or later     Canon NDPS Gateway       Macintosh® 0S 8.0 or later (PPD)     Canon Font Manager       Novell® NetWare® v.3.2, 4.1, 4.11, 4.2,     Canon Watermark Add-in       5, 5.1, 6, 6.5 (IPX/SPX™)     DSE (Device Status Extension)       Printer Drivers     Address Book Conversion Utility       UFR II:     Windows 2000/XP       Windows Server 2003     Citrix MetaFrame		
Macintosh® OS 8.0 or later (PPD)     Canon Font Manager       Novell® NetWare® v.3.2, 4.1, 4.11, 4.2,     Canon Watermark Add-in       5, 5.1, 6, 6.5 (IPX/SPX™)     DSE (Device Status Extension)       Printer Drivers     Address Book Conversion Utility       UFR II:     Windows 2000/XP       Windows Server 2003     Citrix MetaFrame		
Novell® NetWare® v.3.2, 4.1, 4.11, 4.2,     Canon Watemark Add-in       5, 5.1, 6, 6.5 (IPX/SPX™)     DSE (Device Status Extension)       Printer Drivers     Address Book Conversion Utility       UFR II:     Windows 2000/XP       Windows Server 2003     Citrix MetaFrame		
5, 5.1, 6, 6.5 (IPX/SPX™)     DSE (Device Status Extension)       Printer Drivers     Address Book Conversion Utility       UFR II:     Windows 2000/XP       Windows Server 2003     Citrix MetaFrame		
Printer Drivers Address Book Conversion Utility UFR II: Windows 2000/XP Windows Server 2003 Citrix MetaFrame		
UFR II: Windows 2000/XP Windows Server 2003 Citrix MetaFrame		
Windows Server 2003 Citrix MetaFrame		
Citrix MetaFrame		
Macintosh OSX (OS 10.1.5 or later) Other Optional Accessories and Utilities		
PCL 5e/6: Windows 98/Me/2000/XP • Accessibility Handle-A1		
Windows NT 4.0/Server 2003 • Barcode Printing Kit-A1 ** Approximate 3-second-per-page fax transmission time based of		
Citit Metarialite Dialite Label Nit-A1	No. 1 Chart (MMR, Standard Mode) at 33.6 Kbps modem speed when transmitting to another V.34 machine. The Public Switched Telephone	
rss Enluation: Williaws 98/Me/2000/Ar Calu Reader-Ci		
Windows NT 4.0/Server 2003 • Card Reader Attachment-C2 Network (PSTN) currently supports 28.8 Kbps modem speeds	s or lower,	
Macintosh OS X (OS 10.2 or later) • Card Sets depending on telephone line conditions.		



1-800-OK-CANON www.usa.canon.com

Canon U.S.A., Inc. One Canon Plaza Lake Success, NY 11042

LISENC

As an ENERGY STAR<sup>®</sup> Partner, Canon U.S.A., Inc. has determined that these products meet the ENERGY STAR guidelines for energy efficiency. ENERGY STAR and the ENERGY STAR mark are registered U.S. marks. Windows and Windows NT are registered trademarks of Microsoft Corporation in the United States and/or other countries. Adobe and PostScript are registered trademarks of Adobe Systems Incorporated in the United States and/or other countries. Apple and Macintosh are registered trademarks of Apple Computer, Inc. Intel and Celeron are registered trademarks of Intel Corporation. eCopy ShareScan is a trademark of eCopy, Inc. Novell and NetWare are registered trademarks of Novell, Inc. Inte United States and other countries. Solaris is a trademark of Sun Microsystems, Inc. in the United States and other countries. SIM States and other countries. IPX/SPX is a trademark of Novell, Inc. Intel United States and UNIVERSAL SEND and the GENUINE logo are trademarks of Canon Inc. in the United States and use registered trademarks of Canon U.S.A., Inc. In the United States and and y also be registered trademarks of Canon U.S.A., Inc. In the United States and ther countries. IPX/SPX is a trademark of States and is a trademark of Canon Inc. in the United States and JuNIVERSAL SEND and the States and is a trademark of Canon Inc. in certain other countries. Remote Ulis a trademark of Canon U.S.A., Inc. IMAGEANYWARE is a trademark of Canon. All referenced product names and other marks are trademarks of their respective owners. Some products shown with optional accessories and equipment.

Some products shown with optional accessories and equipment. ©2005 Canon U.S.A., Inc. All rights reserved.